

"An error occurred. Please contact administrator." - got error while trying to access remote server from jump server

211 Manu Chacko October 9, 2024 [Common Errors & Troubleshooting](#) 8045

How to solve "An error occurred. Please contact administrator." when accessing the remote server from Ezeelogin?

Overview: This article provides a solution for the error "**An error occurred. Please contact the administrator**" encountered while accessing a remote server from the ezsh shell. This issue is typically caused by permission problems when writing SSH sessions to the `/var/log/ezlogin/` directory. The resolution involves checking the log file for specific errors and correcting the log file permissions using a command.

```
An error occurred. Please contact administrator.  
Connection to 192.168.1.38 closed.
```

Step 1: Check for the [errors](#) in the `/home/{username}/ezsh.log`.

```
root@gateway:~# tail -f /home/<username>/ezsh.log  
  
SSH log file (/var/log/ezlogin/full/john/master~auto-  
test-01.master.eznoc.com~Mon_May_9_12:09:12_2018) creation failed: Permission denied  
  
SSH log file (/var/log/ezlogin/full/john/master~auto-  
test-01.master.eznoc.com~Mon_May_9_22:18:38_2018) creation failed: Permission denied  
  
SSH log file (/var/log/ezlogin/full/john/master~auto-  
test-01.master.eznoc.com~Mon_May_9_22:38:25_2018) creation failed: Permission denied
```

Step 2: Fix the log permission by executing the following command in your gateway server:

```
root@gateway:~# /usr/local/ezlogin/eztool.php -fix_log_permissions
```

Related Articles:

[Unable to open a session.](#)

[An error occurred while accessing the parallel shell.](#)

Online URL:

<https://www.ezeelogin.com/kb/article/an-error-occurred-please-contact-administrator-got-error-while-trying-to-access-remote-server-from-jump-server-211.html>